T 886 357 367 08
F 886 357 387 49
A 7F., No.35, Xuefu Rd., East Dist.,
Hsinchu City 30068, Taiwan

EnzyTek TECHNOLOGY

BTM-QC3083-2

Preliminary Datasheet

(Version 01)

Issued date: November 14, 2023

EnzyTek Bluetooth Module – BTM-QC3083-2

Product Description

BTM-QC3083-2 is a highly integrated small form factor (19x13 mm^2) Bluetooth module which adopts Qualcomm QCC3083 as core chip for Bluetooth operation.

QCC3083 VFBGA is a system on-chip (SoC) with on-chip Bluetooth audio and programmable application processor. It includes high-performance, analog, and digital audio codecs, Class-AB and Class-D headphone drivers, advanced power management, Li-ion battery charger, light-emitting diode (LED) drivers, and flexible interfaces including inter- integrated circuit sound (I^2S), inter-integrated circuit interface (I^2C), universal asynchronous receiver transmitter (UART), and programmable input/output (PIO).

FEATURES

- Highly integrated BT v5.4 QCC3083 module with embedded Balun + Filter + Crystal + Flash
- Bluetooth LE Audio
- 240 MHz Qualcomm® Kalimba™ audio DSP
- 32/80 MHz Developer Processor for applications
- Firmware Processor for system
- High-performance 24-bit stereo audio interface
- Digital and analog microphone interfaces
- Flexible PIO controller and LED pins with PWM support
- Serial interfaces: UART, Bit Serializer (I^2C/SPI), USB 2.0
- Advanced audio algorithms
- Qualcomm® aptX™, aptX™ HD Audio
- aptX Adaptive, enabled using license key
- 1-mic Qualcomm® cVc™ Speaker Noise Cancellation Technology
- Integrated PMU: Dual SMPS for system/digital circuits, Integrated Li-ion battery charger
- Frequency: 2402 ~ 2480 GHz
- TX Output Power: 11 dBm(Max)
- RX Sensitivity: -90 dBm(Max)
- Dimension: 19 mm x 13 mm x 2.8 mm (L x W x H) (Nico checks with latest layout)
- Temperature: -10~+70 ˚C

Applications

- Wired/wireless stereo headsets/headphones wireless stereo speaker/headsets/headphones
- Qualcomm® TrueWireless™ Mirroring stereo speaker
- LE Unicast Audio and broadcast Audio, source and sink, applications.
- Customization FW for unique wireless applications.

Audio subsystem

- 32-bit Kalimba audio digital signal processor (DSP) cores with flexible clocking from 2 MHz to 240 MHz to allow optimization and trade-off performance vs. power consumption
- DSPs execute code from ROM
- OEM and third party developed features can run from program RAM
- 384 KB program RAM and 1024 KB data RAM

Application subsystem

- Dual core application subsystem 32/80 MHz operation
- 32-bit Firmware Processor:
  - Runs Bluetooth upper stack
  - Profiles, house-keeping code
  - House-keeping code
- 32-bit Developer Processor:
  - Developer applications
- Both cores execute code from external flash memory using QSPI clocked at 32 MHz or 80 MHz
- On-chip caches per core allow for optimized performance and power consumption

Bluetooth subsystem

- Qualified to Bluetooth v5.4 specification including 2 Mbps Bluetooth low energy and Bluetooth Low Energy Isochronous Channels
- Qualcomm® Bluetooth High Speed Link
- Single ended antenna connection with on-chip balun and Tx/Rx switch
- Bluetooth, Bluetooth low energy, and mixed topologies supported
- Class 1 support

Li-ion battery charger

- Integrated battery charger supporting:
  - Internal mode (up to 200 mA)
  - External mode (up to 1.8 A)
- Thermal monitoring and management are available in application software

Block Diagram

T 886 357 367 08
F 886 357 387 49
A 7F., No.35, Xuefu Rd., East Dist.,
Hsinchu City 30068, Taiwan

Pinout Diagram & Dimension

Unit: mm

T 886 357 367 08
F 886 357 387 49
A 7F., No.35, Xuefu Rd., East Dist.,
Hsinchu City 30068, Taiwan

I/O PIN LISTING

Pin No.	Pin Name	Type	Description
1	PIO15	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 15. Alternative function: MCLK_OUT
2	PIO16	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 16. Alternative function: PCM_CLK
3	PIO17	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 17. Alternative function: PCM_SYNC
4	PIO18	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 18. Alternative function: PCM_DOUT[0]
5	PIO19	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 19. Alternative function: PCM_DIN[0]
6	PIO20	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 20. Alternative function: PCM_DOUT[1]
7	PIO21	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 21. Alternative function : PCM_DOUT[2]
8	GND	Power	Ground
9	USB_DN	Digital	USB Full Speed device D- I/O.
10	USB_DP	Digital	USB Full Speed device D+ I/O.
11	VCHG	Analog	VCHG voltage input.
12	VCHG_SENSE	Analog	Charger input sense pin after external mode sense-resistor. High impedance. Note : If using internal charger or no charger, connect VCHG_SENSE direct to VCHG.
13	CHG_EXT	Analog	External charger transistor current control. Connect to base of external charger transistor as per application schematic.
14	SYS_CTRL	Digital input	Typically connected to an ON/OFF push button. Boots device in response to a button press when power is still present from battery and/or charger but software has placed the device in the OFF or DORMANT state. Additionally useable as a digital input in normal operation. No pull. Additional function: PIO[0] input only
15	VBAT	Power	Battery voltage input.
16	GND	Power	Ground

17	LED0/AIO0	Analog or digital input/ open drain output.	General-purpose analog/digital input or open drain LED output.
18	LED1/AIO1	Analog or digital input/ open drain output.	General-purpose analog/digital input or open drain LED output.
19	LED2/AIO2	Analog or digital input/ open drain output.	General-purpose analog/digital input or open drain LED output.
20	LED4/AIO4	Analog or digital input/ open drain output.	General-purpose analog/digital input or open drain LED output.
21	LED5/AIO5	Analog or digital input/ open drain output.	General-purpose analog/digital input or open drain LED output.
22	GND	Power	Ground
23	1V8	Power	1.8V output
24	VDD_PADS_6&7	Power	1.8 V/3.3 V PIO supply
25	VDD_PADS_1&3	Power	1.8 V/3.3 V PIO supply
26	PIO2	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 2. Alternative function: TBR_MISO[3]
27	PIO3	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 3. Alternative function: TBR_MISO[2]
28	PIO4	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 4. Alternative function: TBR_MOSI[1]
29	PIO5	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 5. Alternative function: TBR_MISO[1]
30	PIO6	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 6. Alternative function: TBR_MOSI[0]
31	PIO7	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 7. Alternative function: TBR_MISO[0]
32	PIO8	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 8. Alternative function: TBR_CLK
33	PIO1	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Automatically defaults to RESET# mode when the device is unpowered, or in off modes. Reconfigurable as a PIO after boot. Alternative function: Programmable I/O line 1
34	GND	Power	Ground
35	SPK_RN	Analogue out	Headphone/speaker differential right output, negative. Alternative function: Differential right line output, negative

36	SPK_RP	Analogue out	Headphone/speaker differential right output, positive. Alternative function: Differential right line output, positive
37	SPK_LN	Analogue out	Headphone/speaker differential left output, negative. Alternative function: Differential left line output, negative
38	SPK_LP	Analogue out	Headphone/speaker differential left output, positive. Alternative function: Differential left line output, positive
39	GND	Power	Ground
40	MIC_BIAS	Analogue out	Mic bias output.
41	MIC_RN	Analogue in	Microphone differential 2 input, negative. Alternative function: Differential audio line input right, negative
42	MIC_RP	Analogue in	Microphone differential 2 input, positive. Alternative function: Differential audio line input right, positive
43	MIC_LN	Analogue in	Microphone differential 1 input, negative. Alternative function: Differential audio line input left, negative
44	MIC_LP	Analogue in	Microphone differential 1 input, positive. Alternative function: Differential audio line input left, positive
45	GND	Power	Ground
46	GND	Power	Ground
47	BT_RF	RF	Bluetooth transmit/receive.
48	GND	Power	Ground
49	PIO39	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 39. Alternative function: QSPI2_IO[3]
50	PIO38	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 38. Alternative function: QSPI2_CS#
51	PIO37	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 37. Alternative function: QSPI2_IO[1]
52	PIO36	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 36. Alternative function: QSPI2_IO[2]
53	PIO35	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 35. Alternative function: QSPI2_CLK

54	PIO34	Digital: Bidirectional with programmable strength internal pull- up/pull-down	Programmable I/O line 34. Alternative function: QSPI2_IO[0]
55	LED3/AIO3	Analog or digital input/ open drain output.	General-purpose analog/digital input or open drain LED output.

PS: The PIO definition can be customized for the application, please contact with EnzyTek for detail FW specification.

Radio Characteristics

VCC = 3.3V and test under Non-EDR environment

		Min	Typ	Max	Bluetooth Spec.	Unit
Maximum RF transmit power		9	10	11	0 ~ +20	dBm
Sensitivity, 0.1% BER	2.402 GHz			-90	≦-70	dBm
	2.411 GHz			-90		dBm
	2.480 GHz			-90		dBm
RF Power control range			20		≧16	dB
RF Power control resolution		3.3		6.3	2dB≦ step ≦8dB	dBm
20dB bandwidth for modulated carrier			910		≦1000	kHz
△f1avg Max. modulation		155		170	140 < f1avg < 175	kHz
△f2max Min.. modulation		135		175	≧115	kHz
△f1avg / △f2avg		0.9	0.94	1	≧0.80	
Initial Carrier Center Frequency Tolerance		-15		+15	≦±75	kHz
Frequency Drift Rate		-300		300	≦±400	Hz/us
Frequency Drift (single slot packet)		-20	-10	20	≦±25	kHz
Frequency Drift (five slot packet)		-20	-12	20	≦±40	kHz

Battery input pin specification

VBAT	Min	Typ	Max	Unit
Operating voltage	2.8	3.7	4.6	V
Boot voltage	3.0	-	4.6	V
Software power-off threshold	-	3.0	-	V
USB dead/weak battery rising threshold	3.14	3.3	3.46	V
USB dead/weak battery hysteresis	50	-	120	mV

Charger input pin specification

VCHG	Min	Typ	Max	Unit
Operating voltage (full device specification)	4.75	5	5.5	V
Operating voltage (reduced charger specification)	4.0	5	5.5	V
VCHG_PRESENT rising threshold	3.4	3.6	4.0	V
VCHG_PRESENT hysteresis	70	-	150	mV
Full operating range	VCHG_ PRESENT	-	6.5	V
On chip pull-down (disabled when VCHG_PRESENT = 1)	10	20	30	kΩ

- The VCHG pin is tolerant of voltages up to 6.5 V, but the standard specified operating range of the charger is up to 5.5 V. With VCHG at 6.5 V, the typical battery charge current will be approximately 5% greater than at 5.5 V.

Microphone Bias

Parameter	Conditions	Min	Typ	Max	Unit
Output voltage (Tunable, step = 0.1 V)	-	1.5	-	2.1	V
Output current capability	-	0.07	-	6.0	mA
Output noise	B/W = 20 Hz → 20 kHz Unweighted	4.5	5.1	7.3	μVrms
Crosstalk Between Microphones	Using recommended application circuit	-	80	-	dB
Load capacitance [a]	From parasitic PCB routing and package	-	-	0.1	nF

Stereo Codec: Analogue to Digital Converters:

High-quality (HQADC) differential audio input

Parameter	Conditions	Min	Ty	Max	Unit
Output Sample Width	-	-	-	24	Bits
Output Sample Rate, F_{sample}	-	8	-	96	kHz
Input level	-	-	-	2.4	V pk-pk
Input impedance	0 dB to 24 dB analog gain	-	2	-	kΩ
	27 dB to 39 dB analog gain	-	1	-	kΩ
SNR	F_{in} = 1 kHz F_{sample} = 48 kHz Input Amp. = 2.4 V_{pk-pk} B/W = 20 Hz to 20 kHz A-Weighted	-	99 .2	-	dB
THD+N	F_{in} = 1 kHz F_{sample} = 48 kHz Input Amp. = 2.4 V_{pk-pk} B/W = 20 Hz to 20 kHz	-	-95	-	dB
Analog gain	3 dB steps	0	-	39	dB
Stereo separation (crosstalk)	-	80	-	-	dB

Stereo Codec: Digital to Analog Converters:

Class-D DAC audio output

Parameter	Conditions	Min	Typ	Max	Uni
Input Sample Width	-	-	-	24	Bits
Input Sample Rate, F_{sample}	-	8	-	192	kHz
Output Power	0 dBFS, 32 Ω load -3 dBFS, 16 Ω load	-	-	30	mW
Load	-	16	32	30k	Ω
SNR	F_{in} = 1 kHz F_{sample} = 48 kHz Input Amp. = 0 dBFS Analog Gain = 0 dB B/W = 20 Hz to 20 kHz A-Weighted 32 Ω load	-	105.1	-	dB
THD+N	F_{in} = 1 kHz F_{sample} = 48 kHz Input Amp. = 0 dBFS Analog Gain = 0 dB B/W = 20 Hz to 20 kHz A-Weighted 32 Ω load	-	-90.1	-	dB
Max capacitive load	Per terminal to ground	-	-	100	pF

T 886 357 367 08
F 886 357 387 49
A 7F., No.35, Xuefu Rd., East Dist.,
Hsinchu City 30068, Taiwan

Class-AB DAC audio output

Parameter	Conditions	Min	Typ	Max	Uni
Input Sample Width	-	-	-	24	Bit
Input Sample Rate, F_{sample}	-	8	-	192	kHz
Output Power	0 dBFS, 32 Ω load -3 dBFS, 16 Ω load	-	-	30	mW
Load	-	16	32	30k	Ω
SNR	F_{in} = 1 kHz F_{sample} = 48 kHz Input Amp. = 0 dBFS Analog Gain = 0 dB B/W = 20 Hz to 20 kHz A-Weighted 32 Ω load	-	104.8	-	dBA
THD+N	F_{in} = 1 kHz F_{sample} = 48 kHz Input Amp. = 0 dBFS Analog Gain = 0 dB B/W = 20 Hz to 20 kHz A-Weighted 32 Ω load	-	-91.1	-	dB
Stereo separation (crosstalk)	-	80	-	-	dB

PCB Layout Guide

Footprint dimensions

BT Stereo Headset Application Circuit

T 886 357 367 08
F 886 357 387 49
A 7F., No.35, Xuefu Rd., East Dist.,
Hsinchu City 30068, Taiwan

Evaluation board definition

BTM-QC3083-2-DB

Top

Bottom

BTM-QC3083-2-EB

Top

Bottom

1. Micro USB
   Main USB port
2. Button
   SW1=SYS_CTRL, SW2=PIO2, SW3=PIO3, SW4=PIO4, SW5=PIO5
3. Phone Jack

4. DAC/I2S Audio output Switch

5. Current measure

6. Power source
   BT_VDD
   1-2 short : VBAT
   2-3 short : VDD33
   VDD_IO
   1-2 short : 1V8
   2-3 short : 3V3

7. VDD33 Power source

1-2 short : VUSB

2-3 short : VBAT

8. GPIO

PIO4:UART_RX,PIO5:UART_TX

9. TRBI Debug Interface

10. USB Power Jumper (VCHG Source)

11. OLED Interface(PIO20:SCL,PIO21:SDA)

12. LED

LED0: Blue,

LED1: Red

LED2: Green

13. Battery connector

BTM-QC30XX/51XX-MB

1. USB-TYPE C
   Main USB port
2. USB Power source
   1-2 short : USB Type C
   2-3 short : Micro-USB

3. Power Switch
   UP: VDD_33 on or VBAT off.
   Down: VBAT on or power VDD_33 off.
4. TRBI
   Interface for TRBI2000 Tool kit
5. USB-Micro USB
   It must be connected to this port as you use the UART function.
6. GPIO
   Full PIO/AIO test pin.
7. Power source selector
   Header default setting

8. UART
   Header default setting
   BT_TX=PIO5, BT_RX=PIO4
   MB DB

9. VDD_IO
   1-2 short: 1V8
   2-3 short: 3V3

10. I2C(Display)

    Header default setting

    SCL=PIO20, SDA=PIO21

11. Button

    Header default setting:

    Reset=PIO0, SYS_CTRL=PIO1, SW3=PIO2, SW4=PIO3, SW5=PIO4, SW6=PIO5

12. LED

    Header default setting

    LED_G=LED0, LED_B=LED1, LED_R=LED2, LED_O=LED4, LED_W=LED5

13. MIC/LINE IN

    Switch setting

    Left: MIC In

    Right: Line in

14. HP OUT

    1-2 short: PIO15 enable

    2-3 short: 3.3V enable

15. AUX OUT

1-2 short: PIO15 enable

2-3 short: 3.3V enable

Header default setting

BCLK=PIO16, DOUT=PIO, DIN=PIO19, LRCK=PIO17

16. TEM EN/Buzzer/AUX_DET/CC/TEM_S

Header default setting

TEM EN=PIO52, LINE IN_DET=PIO60, Buzzer=PIO61, CC_Type C=LED4,

TEM S=LED5